## 1/16 DIN µP BASED CONTROLLERS





- Excellent measurement precision and regulation stability
- 9 sensors, 4 control actions, 16 alarms all keyboard configurable
- PID action with AT autotuning and ADT autoadaptive functions
- LFA diagnostic function of the regulation loop

## THQ SERIES

The microprocessor-based controllers of the **THQ** series are characterised by remarkable regulation precision, in particular in heat-sealing and thermoforming operations typical of the automatic packaging.

The AT initial autotuning and the ADT permanent autoadaptive functions can both be activated through the PID control action, responding excellently to frequent or fast system variations, as for example in process start and stop.

The panel with single or double display allows the setting of all the controller's values and configurations, such as sensor input, control action and alarm functions, with the possibility to lock the programming on three different safety levels.

The exclusive LFA diagnostic function is able to detect failures along the entire regulation loop, for example thermocouples short-circuit or heating resistance breaking.





## **TECHNICAL DATA**

Power supply:	
Consumption:	or 80-240 Vac ±10% version
•	
Sensor input:	
Management and a	termocouples and Pt100Ω/0°C RTDs
weasurement scale:	selectable in °C or °F degrees with lower and
Duratatana	upper limits, refer to table 1
Precision:	•
	RTD measurement ±0,3% f.s.
	temperature drift 0,01% f.s. / °C of ambient
Data undation	temperature setting and indication ±1 digit
Data updating:	
Data retention:	
Keyboard correction indication:	
1st point action control:	. on/οπ or PID selection, maximum or minimum, with AT initial autotuning and ADT
	permanent autoadaptive functions
Proportional band:	·
Integral time:	,
Derivative time:	
Cycle time:	,
On/off hysteresis:	
1st point output type:	
	trans. PNP 12 Vcc ±20% version
	20 mA short-circuit protection
2nd point alarm action:	•
	+999 °C/°F respect to 1st point, or fixed point
	setting on selected scale, refer to table 2
2nd point output type:	•
Auxiliary functions:	-
	digital filter with an average of 10 measures,
	SW program LOCK with 3 levels
Setting:	. PROG, SET, UP, DOWN push-buttons
Indicators:	. 4 digit red display (10mm height), 4 digit
	green display (7mm height) QD vers. or
	5 LED movement bar (QS), yellow ON1 LED,
	red ON2 LED, green LOCK LED,
	green AT LED
Connection:	terminal block with 10 screw contacts,
	electronic block extractable from panel
Electric protection:	
Mechanical protection:	•
	IP20 - housing
	IP10 - contacts
Housing material:	
Weight:	3
Operating temperature:	
Storage temperature:	
Reference standard:	
Certifications:	. ८८

## **TABLES**

Sensor	°C scales	°F scales	
TR int.	- 150 450	- 200 850	
TR dec.	- 99,9 450	-99,9 850	
TC - E	0 600	0 1100	
TC - J	- 50 760	- 50 1400	
TC - K	- 100 1250	- 150 2300	
TC - L	- 50 760	- 50 1400	
TC - S	0 1700	30 3000	
TC - R	0 1700	30 3000	
TC - T	- 100 400	- 150 750	

Table 1: °C/°F SCALE

Alarm	Fixed pt	Function		
AL20	FP20	deactivate		
AL21	FP21	minimum		
AL22	FP22	maximum		
AL23	FP23	neutral zone on		
AL24	FP24	neutral zone off		
AL25	FP25	minimum*		
AL26	FP26	maximum*		
AL27	FP27	neutral zone on*		
AL28	FP28	neutral zone off*		
totand by first interportion inhibition				

\*stand-by: first intervention inhibition

Table 2: ALARM FUNCTIONS















## **CONNECTIONS**



## **DIMENSIONS**



# **TEMPERATURE CONTROLLERS**

# DATASENSOR

## **MODELS**

MODEL	DISPLAY	POWER SUPPLY	MAIN OUTUT	CODE N°
QS-00	single	12 24 Vdc/Vac	relay	974021000
QS-01	single	12 24 Vdc/Vac	transistor	974021010
QS-10	single	80 240 Vac	relay	974021020
QS-11	single	80 240 Vac	transistor	974021030
QD-00	double	12 24 Vdc/Vac	relay	974031000
QD-01	double	12 24 Vdc/Vac	transistor	974031010
QD-10	double	80 240 Vac	relay	974031020
QD-11	double	80 240 Vac	transistor	974031030

## Distributed by:

## **HEADQUARTERS**

### **DATASENSOR SpA**

via Lavino, 265 - 40050 Monte San Pietro, BO - Italy Tel. +39 051/6765611 • Fax +39 051/6759324 www.datasensor.com • e-mail info@datasensor.com

Datasensor SpA endeavours to continuously improve and renew its products; for this reason the technical data and contents of this catalogue may undergo variations without prior notice. For correct installation and use Datasensor SpA can guarantee only the data indicated in the instruction manual supplied with the products.

Printed in Italy in July 2005 Rev. 02